

## Toner (Accessory for NCT-101)

Multifunctional Tester for RJ-45 LAN Cable, BNC/F coaxial cable, tone generator, talk battery, continuity. It is the useful tool set for electrical appliance contractors in the VDV (Voice/Data/Video) market, professionals in telecommunication, network and digital communications, or general people using home networks and students to be used for network installations, VDV detection and failure diagnosis.

The plastic sensing tip is used to avoid accidental short-circuits, wherein it is provided with volume adjusting Knob, audio frequency signal strength indicator and ear plug for applications in different environment, and it has many different interfaces – RJ45 jack and test pin, and is attached with power shortage indicator and is hand-free to carry for on-site use.

### Features

- Automatic Power-off
- Possibility of headphones connection
- Connection map test: Discontinuity, short circuit, reversed pairs, crossed pairs
- LED signal strength indication
- Transmitter Toner interfaces: RJ45, BNC, Test Leads Cable
- Maximum test cable length of 1000m
- Possibility of identifying and tracing wires or cables with no damage to insulation
- Tracing a tone, cable continuity, polarity, verifying a line
- Adjustable volume control
- Alligator clips to connect open wires and for direct connection of internet and telephone cables

### Technical Specifications

Parameter	Values
Display	15 LED (Toner), 3 LED (Tracker)
Tester Type	Wiring System Tester
Signal Frequency	500...781
Power Supply	1 battery 9V 6F22 (Toner), 1 battery 9V 6F22
Detection	Cable and wire continuity, cables in walls
Voltage Protection	48VDC or 24VAC
Signal Frequency	500Hz~781Hz
Signal Volume	>30dB
Maximum receiver distance	60cm
Maximum Cable length for test	1000 meter

## Ordering Information

Part Code	Description
3C-NCT-101-T	Toner (Accessory for NCT-101)

